

WX 6250 ES



Pramac portable generators range: prompt power assistance to light up, tackle site jobs and property improvement works. A complete range to choose from, for best solution to your remote power needs. When not fixing up around the job site, your Pramac portable generator can be used for emergency power during a power outage.

FEATURES

- OHV engine provides consistent power for multiple applications
- Fuel: Petrol
- Starting Systems: Electric (with battery)
- Low-oil level shutdown automatically safeguards engine from damage
- Engine oil for the first startup supplied in a bottle
- Digital multi meter tracks engine runtime for maintenance intervals
- Fuel gauge allows user to track gasoline levels
- Practical quick user's Starting Instruction (decal)
- AVR Automatic Voltage Regulator
- Kit wheels integrated for easy transportation



Caracteristici principale

Frecvență	Hz	50
Tensiune	V	400/230
Faze		3
Putere pasivă	Watts	6100
Putere continuă	Watts	5500

Putere Monofazica

Tensiune	V	230
Putere pasivă monofazică	Watts	2000
Putere continuă monofazică	Watts	1800




Motor		
Marca		Pramac
Tip		OHV
Emisii de eșapament optimizate pentru 97/68 50Hz (COM)		Stage V
Viteză nominală de funcționare	rpm	3000
Combustibil		Benzină
Sistem de pornire		Electric (+Pornire la sfoara)
Capacitate ulei	l	1.1
Protecție ulei		✓



Alternator	
Sistem de regulare tensiune	AVR

Date dimensionale		
Lungime	(L) mm	800
Lățime	(W) mm	698
Înălțime	(H) mm	620
Greutate fără combustibil	Kg	90
Dimensiuni cutie carton lungime/lățime/înălțime	mm	810x625x607



Autonomia		
Capacitate rezervor combustibil		26
Consum combustibil la @ 50%	l/h	2.17
Timp de funcționare la 50%	h	12



Nivel zgomot		
Nivelul de zgomot garantat (LWA)	dB(A)	97
Nivel de stridență a zgomotului la 7 mt	dB(A)	69

PANOURI DE CONTROL GENSET

Montat pe genset și conținând: instrumentație, control, protecție a setului generator și prize.

COMENZI:

- Porniți comutatorul de selectare cu tasta: OFF - ON - START

INSTRUMENTAȚIE

- Voltmetru
- Contor orar
- Aparat de măsurare a frecvenței
- Indicator al nivelului de combustibil

PROTECȚII:

- Ruptor circuit termal
- Protector ulei

PRIZE

SCHUKO 230V 16A IP44	2
3P+N+T CEE 400V 16A IP44	1



The information is aligned with the Data file at the time of download. Printed on 17/01/2021 (ID 10494)

©2021 | PR INDUSTRIAL s.r.l. | All rights reserved | Image shown may not reflect actual package. Specifications subject to change without notice

